

# MAGEWELL

## Pro Convert for NDI<sup>®</sup> to AIO Technical Specifications

Copyright (c) 2011–2023 [Nanjing Magewell Electronics Co., Ltd.](#) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

HDMI, the HDMI logo and High-Definition Multimedia interface are trademarks or registered trademarks of HDMI Licensing LLC. NDI is trademark or registered trademark of NewTek Inc.

Revised on 28/02/2023

### HDMI Output

- Max output: 1920x1080p60
- Delivery video within 2K at the preferred video format according to the EDID of the connected monitor
- Support YUV BT.601, YUV BT.709 signal
- Support 48KHz 8-channel audio output
- HDMI interface: HDMI 1.4

### SDI Output

- Max output: 1920x1080p60. Supported output formats are:
  - 1920x1080p 23.98/24/25/29.97/30/50/59.94/60
  - 1920x1080i 50/59.94/60
  - 1280x720p 23.98/24/25/29.97/30/50/59.94/60
  - 720x576i50
  - 720x480i59.94
- Support YUV BT.601/709 signal
- Support 48KHz 8-channel audio output
- SD/HD/3G-SDI BNC output
- Support SD (ST 259)/HD (ST 292)/3Ga (ST 425)/3Gb (ST 425)/3Gb-DL (ST 425)/3Gb-DS (ST 425) SDI standards
- Output 3G-SDI signal and transmitted distance at 130m (427ft)

### Decoding Features

- Decoding up to 2Kp60 streams of Full NDI, NDI<sup>®</sup>|HX, NDI<sup>®</sup>|HX2, NDI<sup>®</sup>|HX3, RTSP, HTTP, HLS, RTMP Pull/Push, and MPEG-TS over UDP/SRT/RTP protocols
- Simultaneously decode and output HDMI and SDI signals
- H.264/H.265 video decoders
- AAC/MP3 audio decoders
- Support NDI 5.x

### Configuration Management

- Register with Magewell Cloud
- Remote control via WebUI and Magewell Cloud
- Provide comprehensive information regarding the device and decoded signals in real-time
- Allow to configure how a signal is decoded and output, including OSD settings, deinterlacing, resolutions, audio gain, sample rate, and channel mapping, as well as the network connection
- Update firmware
- Support USB RNDIS/ECM
- Support IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provide HTTP APIs

### On-board Control Buttons

- MENU: press to display the menu, or cycle through the options
- SELECT: press to display the menu, enter current option, or confirm the selection
- 16 Position Rotary DIP Switch: set board-index from 0 to F

### Network Interfaces

- 10/100/1000Mbps Ethernet
- IEEE 802.3af PoE

## USB Interface

- USB2.0 Type B
  - 5V/2.1A power supply
  - USB RNDIS/ECM

## LED Indicators

- Power LED status indicator
  - On: power connected
  - Off: power unconnected
- Decode LED status indicator
  - On: decoding
  - Blinks: decoding error
  - Off: source unselected

## Form Factor

- 100.9mm (L) x 60.2mm (W) x 23.3mm (H)

## Accessories

- USB 2.0 A to B cable
- 5V/2.1A power adaptor
- L-bracket

## Screw Mounting Hole

- ¼–20 threaded hole

## Power Consumption

- 5V max current: ~1.05A
- Max power consumption: ~5.5W

## Working Environment

- Operating temperature: 0 to 40 deg C
- Storage temperature: –20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing