

MAGEWELL

Pro Convert HDMI 4K Plus Technical Specifications

Copyright (c) 2011–2018 [Nanjing Magewell Electronics Co., Ltd.](http://www.magewell.com) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

HDMI, the HDMI logo and High-Definition Multimedia interface are trademarks or registered trademarks of HDMI Licensing LLC. Windows, DirectShow and DirectSound are trademarks or registered trademarks of Microsoft Corporation. OS X and macOS are trademarks or registered trademarks of Apple Inc. NDI is trademark or registered trademark of NewTek Inc.

Revised 6/9/2018

Supported Web Browser (tested)

- Microsoft Internet Explorer 11
- Microsoft Edge
- Mozilla Firefox version 61 and above
- Google Chrome version 49 and above
- Apple Safari 11.1 and above
- Opera 55.0.2994.44 and above

Supported Software (tested)

- OBS
- XSplit
- vMix
- VidBlasterX
- Wirecast
- streamstar SW
- mimoLive
- Any other NewTek NDI[®] based encoding or streaming software

Input Interfaces

- HDMI
 - DVI-D 1.0
 - HDMI 1.4
 - HDMI 2.0

Loop-through Interface

- HDMI
 - DVI-D 1.0
 - HDMI 1.4
 - HDMI 2.0

Output Interface

- SD Card (functions to be developed)

PTZ Control

- Mini-DIN–8 jack

Screw Mounting Hole

- ¼–20 mounting hole

Network Interfaces

- 10/100/1000Mbps Ethernet
- IEEE 802.3af PoE

USB Interface

- USB2.0 Type B
- 5V/2.1A power supply
- USB RNDIS

Input feature

- Support for input video resolutions up to 4:4:4 8-bit 4096x2160 60fps

HDMI Specific Features

- 600MHz HDMI receiver
- Adaptive HDMI equalizer
- Support for customized EDID
- Support for extraction of AVI/Audio InfoFrames
- Full colorimetry support
- Support for up to 4096x2160 4:4:4 60fps input signals
- Support for 8 channel IEC60958 audio streams
- Support for extraction of audio formation information & channel status data
- Support for extraction of video timing information
- Support for extraction of 3D format information
- Support for Side-by-Side Half, Top-and-Bottom, Frame Packing 3D mode.

NDI[®] Output Format

- Support for 4:2:2 8-bit output
- Support for up to 4096x2160 60fps or 1920x1080 240fps
- Support for NDI 3.5

Video Processing Features

- Video processing pipelines with 4096x2160 60fps
- Video brightness, contrast, saturation, hue adjustment
- Video de-interlacing
 - Top field only
 - Bottom field only
- Video aspect ratio conversion
 - Auto or manual selection of output aspect ratio
- Video color format conversion
 - Auto or manual selection of input color format & quantization range
 - Auto or manual selection of output color format, quantization range & saturation range
 - Support for RGB, YUV BT.601, YUV BT.709, YUV BT.2020 input color formats
 - Support for YUV BT.601, YUV BT.709, YUV BT.2020 output color formats
 - Support for Limited or Full quantization range
 - Support for Limited, Full & 'Extended gamut' saturation range
- Video frame rate conversion
- Video mirror flip

NDI[®] Source Name

- Support for setting the device name shown in the system using Web UI. By default, the device name is 'Pro Convert

HDMI 4K+’.

- Support for setting the source name shown in the system using Web UI. By default, the source name is ‘board-index + serial number’.
- Support for setting board-index, from 0 to F, through on-board rotary switch

Firmware Upgrade

- Support for manual update using Web UI

LED Indicator

- Status LEDs indicate:
 - the state of power supply: on/off
 - Tally: preview/program
 - the state of input signal: locked/unlocked
 - the state of loopthrough signal: loopthrough connected and signal detected/undetected

Form Factor

- 117.5mm (L) x 66.7mm (W) x 23.4mm (H)

Accessories

- USB2.0 A to B Cable
- 5V/2.1A power adaptor

Power Consumption

- 5V max current: ~2A
- Max power consumption: ~10W

Working Environment

- Operating temperature: 0 to 45 deg C
- Storage temperature: -20 to 70 deg C
- Relative Humidity: 5% to 90% non-condensing