Pro Convert SDI 4K Plus Technical Specifications

Copyright (c) 2011–2026 Nanjing Magewell Electronics Co., Ltd. All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

NDI® is trademark or registered trademark of Vizrt NDI AB.

Revised on 06/18/2026

Input & Loop through Features

- Max video input & loop through: 4096x2160 30fps. Supported inputs include:
  - 4096x2160p/3840x2160p 23.98/24/25/29.97/30
  - 2048x1080p/1920x1080p 23.98/24/25/29.97/30/47.95/48/50/59.94/60
  - 2048x1080i/1920x1080i 23.98/24/25/29.97/30/47.95/48/50/59.94/60
  - 1280x720p 50/59.94/60
  - 720x576 25p/50i (PAL SD)
  - 720x480 29.97p/59.94i (NTSC SD)
- Support RGB/RGBA/YUV/YUVA signals with 10/12-bit color depth
- Support RGB 4:4:4, YCbCr 4:4:4, YCbCr 4:2:2 color sampling
- Support RGB, YUV BT.601/709/2020 video input
- 16-channel SDI embedded audio inputs
- SD/HD/3G/6G-SDI BNC input & loop through
- Support SD (ST 259)/HD (ST 292)/3Ga (ST 425)/3Gb (ST 425)/3Gb-DL (ST 425)/3Gb-DS (ST 425)/6G (ST 2081) SDI standards
- Receive 6G-SDI transmitted up to 100m (328ft)

NDI® Encoding Features

- Encoding NDI High Bandwidth real-time stream at up to 4096x2160 60fps 4:2:2 8-bit
- Output the same resolution as input or any custom resolution. Typical outputs include:
  - 4096x2160p/3840x2160p/2048x1080p/1920x1080p 23.98/24/25/29.97/30/47.95/48/50/59.94/60
  - 2048x1080i/1920x1080i 25/29.97/30/47.95/48/50/59.94/60
  - 1280x720p 50/59.94/60
- Output frame rate same as the original, 1/2, 1/3 or 1/4 of input frame rate
- Support HDR HLG
- Encoding 16-channel NDI-embedded audio
- Support NDI 6.2

Configuration Management

- Register with Control Hub
- Remote control via WebUI and Control Hub
- Provide comprehensive information regarding the device and signals in real-time
- Allow to configure how an input is processed and encoded, including deinterlacing, up/down scaling, frame rate, aspect ratio, as well as the network connection
- Update firmware
- Support USB RNDIS/ECM
- Support IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provide HTTP APIs

On-board Control Buttons

- 16 Position Rotary DIP Switch: set board-index from 0 to F

PTZ Control

- Control PTZ cameras using protocols of VISCA, Visca UDP, Visca UDP2rs232, PELCO-P and PELCO-D via NDI
- Mini-DIN–8 jack (shared with Tally light)

Network Interfaces

- 10/100/1000Mbps Ethernet
- IEEE 802.3af PoE

USB Interface

- USB2.0 Type B
  - 5V/2.1A power supply
  - USB RNDIS/ECM

Supported Products

- NDI Studio Monitor
- OBS
- vMix
- Any other NDI-enabled product

LED Indicators

- Status LEDs indicate:
  - Power supply: on/off
  - Tally: preview/program
  - Input signal: locked/unlocked
  - Loop through signal: on/off

Form Factor

- 117.5mm (L) x 66.7mm (W) x 23.4mm (H)

Accessories

- USB 2.0 A to B cable
- 5V/2.1A power adaptor
- Mini-DIN 8 breakout cable
- Tally light
- L-bracket

Screw Mounting Hole

- ¼–20 threaded hole

Power Consumption

- 5V max current: ~1.5A
- Max power consumption: ~7W

Working Environment

- Operating temperature: 0 to 45 deg C
- Storage temperature: –20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing