

# MAGEWELL

## Pro Convert SDI Plus Technical Specifications

Copyright (c) 2011–2020 [Nanjing Magewell Electronics Co., Ltd.](#) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

Windows, DirectShow and DirectSound are trademarks or registered trademarks of Microsoft Corporation. OS X and macOS are trademarks or registered trademarks of Apple Inc.

Revised 29/05/2020

### Supported Web Browser

- Microsoft Internet Explorer 11
- Microsoft Edge
- Mozilla Firefox version 61 and above
- Google Chrome version 49 and above
- Apple Safari 11.1 and above
- Opera 55.0.2994.44 and above

### Supported Software

- OBS
- XSplit
- vMix
- VidBlasterX
- Wirecast
- streamstar SW
- mimoLive
- Any other NewTek NDI-enabled encoding or streaming software

### Input Interfaces

- BNC
  - SD/HD/3G SDI

### Loop-through Interface

- BNC
  - SD/HD/3G SDI

### Storage Interface

- SD Card (functions to be developed)

### PTZ + TALLY Control

- Mini-DIN-8 jack

### Screw Mounting Hole

- ¼-20 mounting hole

### Network Interfaces

- 10/100/1000Mbps Ethernet
- IEEE 802.3af PoE

### USB Interface

- USB2.0 Type B
- 5V/2.1A power supply
- USB RNDIS/ECM

## Input feature

- Support for up to 2048x1080 60fps input resolution

## SDI Specific Features

- Integrated cable equalizer extending the cable length as follows:
  - up to 330m for SD-SDI signals
  - up to 300m for HD-SDI signals
  - up to 200m for 3G-SDI signals
- Support for SD/HD/3Ga/3Gb/3Gb-DL/3Gb-DS (SMPTE 2081) standards
- Support for RGB 4:4:4, YCbCr 4:4:4, YCbCr 4:2:2 color sampling
- Support for 10/12-bit color depth
- Support for extraction of SMPTE 352 payload identifier
- Support for up to 16 (mono) audio channels
- Support for extraction of audio formation information & channel status data
- Limited support of 3Gb-DS: only the first stream can be captured
- Limited support for capture of the first link of dual link interfaces:
  - YCbCr 4:2:2 10-bit 1080p 50/59.94/60: captured as 1080i 50/59.94/60
  - YCbCr 4:4:4 10-bit: captured as 4:2:2
  - RGB 4:4:4: R/B sub-sampled

## NDI<sup>®</sup> Output Format

- Support for 4:2:2 8-bit output
- Support for up to 2048x1080 60fps output resolution
- Support for NDI 4.1

## Video Processing Features

- Support for capture resolutions up to 2048x1080
- Video brightness, contrast, saturation, hue adjustment
- Video de-interlacing
  - Top field only
  - Bottom field only
- Video aspect ratio conversion
  - Auto or manual selection of output aspect ratio
- Video color format conversion
  - Auto or manual selection of input color format & quantization range
  - Auto or manual selection of output color format, quantization range & saturation range
  - Support for RGB, YUV BT.601, YUV BT.709, YUV BT.2020 input color formats
  - Support for YUV BT.601, YUV BT.709, YUV BT.2020 output color formats
  - Support for Limited or Full quantization range
  - Support for Limited, Full & 'Extended gamut' saturation range
- Video frame rate conversion
- Video mirror flip

## NDI<sup>®</sup> Source Name

- Support for setting the device name shown in the system using Web UI. By default, the device name is 'Pro Convert'.
- Support for setting the source name shown in the system using Web UI. By default, the source name is 'board-index + serial number'.
- Support for setting board-index, from 0 to F, through the on-board rotary switch

## Firmware Upgrade

- Support for manual update using Web UI

## LED Indicator

- Status LEDs indicate the working state of the device:
  - Power supply: on/off
  - Tally: preview/program
  - Input signal: locked/unlocked
  - Loophrough signal: loophrough connected and signal detected/undetected

## **Form Factor**

- 117.5mm (L) x 66.7mm (W) x 23.4mm (H)

## **Accessories**

- USB 2.0 A to B Cable
- 5V/2.1A power adaptor
- Mini-DIN-8 (PTZ + TALLY) to RS232 (PTZ) + Mini-DIN-8 (TALLY)
- Tally lights
- L-bracket
- LED matrix panel (optional)

## **Power Consumption**

- 5V max current: ~1.5A
- Max power consumption: ~6W

## **Working Environment**

- Operating temperature: 0 to 45 deg C
- Storage temperature: -20 to 70 deg C
- Relative Humidity: 5% to 90% non-condensing