

Pro Convert for NDI to HDMI Module Technical Specifications

Converts a live IP stream into HD HDMI signal

SKU: B41010000

Product Overview

Pro Convert for NDI® to HDMI Module is a hot-swappable module to be installed in the Magewell Modator chassis. It is capable of decoding IP streams up to 2Kp60 in a wide range of formats (including NDI® High Bandwidth, NDI® HX2, NDI® HX3, TVU ISSP, RTMP, RTSP, HLS, MPEG-TS and more) into HDMI output, which provides a higher-density product form factor and a scalable solution for IP-based production and distribution deployments.

Key Features

- Support for up to 4096x2160 60fps HDMI output
- Support 48KHz, 8-channel audio output
- Decode up to 2Kp60 NDI® streams as well as additional protocols including RTSP, HTTP, HLS, RTMP Pull/Push and MPEG-TS over UDP/SRT/RTP and TVU ISSP
- Discover NDI® devices across network segments
- Support NDI® 6.2
- Image flip for inverted projector installations and safe area controls
- Automatic output optimization for target display with integrated up/down conversion
- Configure through the touch screen of Magewell Modator chassis, Web GUI or Control Hub

Technical Specifications

Revised on 01/29/2026

Interfaces

- 1* RJ45 1000Mbps Ethernet port
- 1* USB Type-C port for configuration
- 1* USB Type-A 3.0 port for connecting peripherals
- 1* HDMI 2.0 output port
- 1* Modator interface for connecting to Modator 2U (hot-swappable)

Decoding Features

- Decode up to 2Kp60 streams of NDI High Bandwidth , NDI® |HX, NDI® |HX2, NDI® |HX3, RTSP, HTTP, HLS, RTMP Pull/Push, MPEG-TS over UDP/SRT/RTP, TVU protocols
- Decode SpeedHQ/H.264/H.265 video
- Decode AAC/MP3 audio
- Supports NDI® 6.2

Output Features

- Max. output: 4096x2160 60fps 4:4:4 8-bit
- Deliver video at the preferred video format according to the EDID of the connected monitor. Supported output formats include:
 - 4096x2160p/3840x2160p 23.98/24/25/29.97/30/50/59.94/60
 - 2560x1440p 60/100
 - 2560x1080p 23.98/24/25/29.97/30/50/59.94/60
 - 1920x1080p 23.98/24/25/29.97/30/50/59.94/60/100/119.88/120
 - 1920x1080i 50/59.94/60
 - 1280x720p 23.98/24/25/29.97/30/50/59.94/60
 - 720x576p50
 - 720x576i50
 - 720x480p59.94/60
 - 720x480i59.94/60

- Supports RGB, YUV444, and YUV422 signals
- Supports 48KHz 8-channel audio output

Web UI

- Register with Magewell Control Hub for remote centralized management
- Supports configuring and managing via Web UI
- Provides comprehensive information regarding the device and decoded signals in real-time
- Allow to configure how a signal is decoded and output, including OSD settings, deinterlacing, resolutions, audio gain, sample rate, and channel mapping, as well as the network connection
- Supports updating firmware
- Supports USB RNDIS/ECM
- Supports IE/Edge/Firefox/Chrome/Safari/Opera web browsers
- Provides HTTP APIs

LED Indicators

- Decode status indicator
 - On: decoding
 - Blinks: decoding error
 - Off: source unselected

Physical Specifications

- Form factor: 184.4mm (L) x 30.0mm (W) x 81.5mm (H)
- Weight: ≈290g

Power Consumption

- Max power consumption: 4.3W

Working Environment

- Operating temperature: 0 to 50 deg C
- Storage temperature: -20 to 70 deg C
- Relative humidity: 5% to 90% non-condensing

Notice

Copyright (c) 2011–2026 [Nanjing Magewell Electronics Co., Ltd.](#) All rights reserved.

Specifications are based on current hardware, firmware and software revisions, and are subject to change without notice.

“MAGEWELL” is registered trademark by Magewell. All other trademarks are the property of their respective holders.